## DYDEN CORPORATION

ELECTRIC WIRES & CABLES PRODUCTS

<u>DATE</u> Feb, 29, 2016 <u>SPEC.</u> No.FSC16-106

## SPECIFICATION

FOR

CROSS-LINKED POLYETHYLENE (XLPE) INSULATED AND PVC JACKETED CABLE WITH SHIELD

(RMCV - SB - Kr(2464))

RoHS correspondence



signed by S. Maeda S. MAEDA

Manager
Engineering section
Engineering dept
Factory Automation & Robot Cable Division

#### 1. SCOPE

This specification covers the construction, characteristics of the Cross-Linked Polyethylene(XLPE) insulated and PVC jacketed cable with shield.

#### 2. SYMBOL, SIZE

The symbol and size of the cable shall be '' RMCV-SB-Kr (2464)  $$\rm AWG25/2C$  ''  $$\rm (0.2mm^2/2C)$$ 

#### 3. UL STANDARD

RECONGNIZED by UNDERWIRITERS LABORATORIES Inc.

STYLE No.	2464 (UL 758 : AWM)	
Rating TEMP.	80℃	
VOLT.	$300\mathrm{V}$	
USE	Internal wiring or external interconnection	
	of electronic equipment	

#### 4. FLAME TESTING

The cable shall pass the vertical wire flame test (VW-1) described in UL1581, Paragraph 1080.

#### 5. CONSTRUCTION

The construction of the cable shall conform to Table 1.

#### 6. CHARACTERISTICS

The characteristics of the cable shall be shown in Table 2.

#### 7. MARKING

The following information shall be indicated with a suitable method to the cable.

" — DYDEN E91337 **N** AWM 2464 80C 300V VW-1 -LF- RMCV-SB-Kr AWG25/2C — "

\* \* \* \* \* \* \* \* \* \* \* \* \* \* \* \* \*

Table 1 Construction


I T E M		V A L U E
Symbol		RMCV-SB-Kr (2464)
Size	AWG (mm²)	25 (0.2)
Conductor	Material	Annealed Copper
	Construction (No./mm)	40/0.08
	Dia. (approx.mm)	0. 58
Insulation	Material	XLPE
	Thickness(approx.mm)	0. 20
	Dia. (approx.mm)	0. 98
Stranding	Center layer	2 C
Tape	1	Binder tape
Shield (Braid)	Material	Tinned Annealed Copper
	Thickness(approx.mm)	0. 25
Jacket	Material(color)	Flame retardant • Oil resistant PVC (Black)
	Thickness(approx.mm)	1.0
Overall diameter(approx.mm)		4. 8
Approx. mass(kg/km)		35

Table 2 Characteristics (at 20°C)

I T E M	STANDARD VALUE
Max.DC resistance of conductor( $\Omega/km$ )	101. 9
Min.insulation resistance (M $\Omega$ -km)	100
Dielectric strength (V/min)	AC 2000

# <u>Fig 1</u>

### <u>Cross-Section of Cable</u>



CoreNo.	Colors
1	Black
2	White